

8 digital inputs, high-speed counter/shaft encoder input, 6 pnp outputs, I/O expansion port, RS232

Power supply	24VDC
Permissible range	20.4 to 28.8VDC
Maximum current consumption	90mA @ 24VDC
Typical power consumption	2W @ 24VDC
	_
Digital inputs	8 pnp (source) inputs
Nominal input voltage	24 VDC
Input voltage	< 5 VDC for Logic '0'
	> 15 VDC for Logic '1'
Input current	3 mA @ 24 VDC
Input impedance	8.4kΩ
Response time	
'0' to '1'	5 mS
'1' to '0'	10 mS
Galvanic isolation	None
Input cable length	Up to 100 meters, unshielded
High-speed counter	Input#7 can be used as either a
High-speed counter	 Input#7 can be used as either a digital input, or as a counter
High-speed counter	•
High-speed counter	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset
High-speed counter	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be
	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder
High-speed counter Resolution	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be
Resolution Input frequency (counter mode)	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder 16-bit Input#6 and input#7 : 5kHz max.
Resolution	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder
Resolution Input frequency (counter mode)	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder 16-bit Input#6 and input#7 : 5kHz max.
Resolution Input frequency (counter mode)	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder 16-bit Input#6 and input#7 : 5kHz max.
Resolution Input frequency (counter mode) Minimum pulse width (counter mode) Digital outputs Output type	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder 16-bit Input#6 and input#7 : 5kHz max. Input#6 and input#7 : 80µs 6 pnp (source) outputs, 24 VDC P-MOSFET (open drain)
Resolution Input frequency (counter mode) Minimum pulse width (counter mode) Digital outputs Output type Isolation	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder 16-bit Input#6 and input#7 : 5kHz max. Input#6 and input#7 : 80µs 6 pnp (source) outputs, 24 VDC P-MOSFET (open drain) None
Resolution Input frequency (counter mode) Minimum pulse width (counter mode) Digital outputs Output type	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder 16-bit Input#6 and input#7 : 5kHz max. Input#6 and input#7 : 80µs 6 pnp (source) outputs, 24 VDC P-MOSFET (open drain) None 0.5A max.
Resolution Input frequency (counter mode) Minimum pulse width (counter mode) Digital outputs Output type Isolation Output current	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder 16-bit Input#6 and input#7 : 5kHz max. Input#6 and input#7 : 80µs 6 pnp (source) outputs, 24 VDC P-MOSFET (open drain) None 0.5A max. Total current: 3A max.
Resolution Input frequency (counter mode) Minimum pulse width (counter mode) Digital outputs Output type Isolation	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder 16-bit Input#6 and input#7 : 5kHz max. Input#6 and input#7 : 80µs 6 pnp (source) outputs, 24 VDC P-MOSFET (open drain) None 0.5A max. Total current: 3A max. 1kHz (resistive load)
Resolution Input frequency (counter mode) Minimum pulse width (counter mode) Digital outputs Output type Isolation Output current	digital input, or as a counter Input#6 can be used as either a digital input or as a counter reset Inputs#6 and #7 can also be used as a shaft encoder 16-bit Input#6 and input#7 : 5kHz max. Input#6 and input#7 : 80µs 6 pnp (source) outputs, 24 VDC P-MOSFET (open drain) None 0.5A max. Total current: 3A max.

Display	STN, LCD display
Illumination	LED yellow-green backlight
Display size	1 line, 16 characters long
Character size	5 x 7 matrix, 3.07 x 5.73mm
	·
Keypad	Sealed membrane
Number of keys	15
PLC program	2048 words
Bits/Coils	256
Integers/Registers	256
Timers	64
Execution time	12µsec. for bit operations
HMI displays	80 user-designed displays
HMI variables	50 HMI variables are available to
	conditionally display and modify text,
	numbers, dates, times & timer
	values. The user can also create a
	list of up to 120 variable text
	displays, totaling up to 2K.
RS232 serial port	
Programming	Download user program
Network option	Via RS485/RS232 converter
I/O expansion port	Up to 64 additional I/Os, including:
	digital & analog I/Os, RTD and more.
Miscellaneous	
Clock (RTC)	Date and time-year 2000 compliant,
	with typical 7 year battery back-up
Weight	260g (9.1 oz.)
Temperature	Operational 0 to +50°C
	Storage -20 to +60°C
Mounting method	DIN-rail mounted (IP20)
	Panel mounted (IP65)



